

On the description of vector bosons.

K. S. Karplyuk^{1,*}

¹*Department of Radiophysics, Taras Shevchenko University,
Academic Glushkov prospect 2, building 5, Kyiv 03122, Ukraine*

A new way of describing massive vector bosons is proposed. It is possible to change the boson propagator in such way that the theory with the vector boson interaction becomes a renormalized one. One example of the efficacy of such a description is shown using the example of the weak interaction of charged currents.

PACS numbers: 12.15.-y, 13.66.-a, 14.80.Hv

The Proca equation is usually used for the description of massive vector bosons:

$$\partial_\mu F^{\mu\nu} + \kappa^2 X^\nu = j_e^\nu. \quad (1)$$

Where, $\kappa = m/\hbar c$,

$$F^{\mu\nu} = \partial^\mu X^\nu - \partial^\nu X^\mu, \quad (2)$$

X^ν is the vector potential, which is determined by the equation

$$\partial_\alpha \partial^\alpha X^\nu + \kappa^2 X^\nu = j_e^\nu + \frac{1}{\kappa^2} \partial^\nu \partial_\mu j_e^\mu. \quad (3)$$

However, Eqs. (1)-(3) lead to unacceptable results. The propagator of the boson described by Eq. (1) has the form

$$D_{\mu\nu} = -\frac{\eta_{\mu\nu}}{k^2 - \kappa^2} + \frac{1}{k^2 - \kappa^2} \frac{k_\mu k_\nu}{\kappa^2}, \quad (4)$$

where $\eta_{\mu\nu} = \text{diag}(1, -1, -1, -1)$, and k_μ is the wave vector. The second term on the right-hand side of Eq. (4) is the offending term and makes the theory with the boson interaction a non-renormalized one. To save renormalization, in the Weinberg-Salam electroweak model the contribution from the second term is compensated for by the contribution from the hypothetical Higgs bosons.

It should be noted that the second term in Eq. (4) is associated with the non-conserved current in Eq. (3). If the current is conserved, $\partial_\mu j_e^\mu = 0$, and this term is absent.

We propose another way to eliminate the second term in Eq. (4). To describe the vector bosons let us use the equation

$$\partial^\nu \epsilon + \partial_\mu F^{\mu\nu} + \kappa^2 X^\nu = j_e^\nu \quad (5)$$

instead of the Proca equation. Where the scalar field ϵ is given by:

$$\epsilon = \partial_\alpha X^\alpha. \quad (6)$$

In this case the potential is given by the equation

$$\partial_\alpha \partial^\alpha X^\nu + \kappa^2 X^\nu = \square X^\nu + \kappa^2 X^\nu = j_e^\nu, \quad (7)$$

where $\square = c^{-2} \partial^2 / \partial t^2 - \Delta$ is the d'Alambertian. The propagator of the boson described by equations (5), and (7) has the form

$$D_{\mu\nu} = -\frac{\eta_{\mu\nu}}{k^2 - \kappa^2}. \quad (8)$$

Thus, the introduction of the scalar field ϵ improves the propagator (4). The propagator (8) is only different from the photon one by the mass in the denominator. It allows continuous transition to the massless boson, and coincides with the photon propagator when $k \rightarrow \infty$. The most important consequence is that the theory based on such propagator becomes renormalized.

The necessity of introduction of the scalar field ϵ is associated with a non-conserved current, but not associated with the mass of the bosons. Differentiation of Eq. (5) yields the equation for the scalar field ϵ :

$$\partial_\nu \partial^\nu \epsilon + \kappa^2 \epsilon = \partial_\nu j_e^\nu. \quad (9)$$

As one can see the scalar field ϵ is generated only by a non-conserved current, which does not satisfy the equation of continuity

$$\partial_\nu j_e^\nu = 0. \quad (10)$$

We must note that should the electric charge not be conserved, it will also be necessary to change Maxwell's equations in a similar way.

The above consideration of the vector boson description can be extended to the pseudovector bosons. To describe them we propose to use the equation

$$\partial^\kappa \beta + \frac{1}{2} \epsilon^{\kappa\lambda\mu\nu} \partial_\lambda F_{\mu\nu} + \kappa^2 Y^\kappa = j_m^\kappa, \quad (11)$$

where

$$\beta = \partial_\nu Y^\nu, \quad F^{\kappa\lambda} = \epsilon^{\kappa\lambda\mu\nu} \partial_\mu Y_\nu. \quad (12)$$

Potential Y^ν is given by the same equation as potential X^ν :

$$\partial_\alpha \partial^\alpha Y^\nu + \kappa^2 Y^\nu = \square Y^\nu + \kappa^2 Y^\nu = j_m^\nu. \quad (13)$$

*Electronic address: ozhmudsky@physics.ucf.edu

Description of vector and pseudovector bosons with the same mass can be combined. It is useful to do, because the weak interaction is just $V - A$ character. We can introduce such a joint description if we associate the field $F^{\mu\nu}$ with the two potentials X^ν and Y^ν simultaneously,

$$F^{\kappa\lambda} = \partial^\kappa X^\lambda - \partial^\lambda X^\kappa + \varepsilon^{\kappa\lambda\mu\nu} \partial_\mu Y_\nu, \quad (14)$$

and use both the Eqs. (5) and (11). We write down these equations in three-dimensional form:

$$\frac{1}{c} \frac{\partial \epsilon}{\partial t} + \nabla \cdot \mathbf{E} - \varkappa V^0 = \zeta c \rho_e, \quad (15)$$

$$\frac{1}{c} \frac{\partial \mathbf{E}}{\partial t} - \nabla \times \mathbf{\mathfrak{B}} + \nabla \epsilon + \varkappa \mathbf{V} = -\zeta \mathbf{j}_e, \quad (16)$$

$$-\frac{1}{c} \frac{\partial \beta}{\partial t} + \nabla \cdot \mathbf{\mathfrak{B}} + \varkappa U^0 = -\zeta c \rho_m, \quad (17)$$

$$\frac{1}{c} \frac{\partial \mathbf{\mathfrak{B}}}{\partial t} + \nabla \times \mathbf{E} - \nabla \beta - \varkappa \mathbf{U} = \zeta \mathbf{j}_m. \quad (18)$$

Here,

$$\mathbf{E} = -\frac{1}{c} \frac{\partial \mathbf{X}}{\partial t} - \nabla X^0 + \nabla \times \mathbf{Y}, \quad (19)$$

$$\mathbf{\mathfrak{B}} = \frac{1}{c} \frac{\partial \mathbf{Y}}{\partial t} + \nabla Y^0 + \nabla \times \mathbf{X}, \quad (20)$$

$$\epsilon = \frac{1}{c} \frac{\partial X^0}{\partial t} + \nabla \cdot \mathbf{X}, \quad V^0 = -\varkappa X^0, \quad \mathbf{V} = -\varkappa \mathbf{X}, \quad (21)$$

$$\beta = \frac{1}{c} \frac{\partial Y^0}{\partial t} + \nabla \cdot \mathbf{Y}, \quad U^0 = -\varkappa Y^0, \quad \mathbf{U} = -\varkappa \mathbf{Y}. \quad (22)$$

The three-dimensional coordinates of the vectors and tensors are given by the rules: $\mathbf{E} = (F_{01}, F_{02}, F_{03})$, $\mathbf{\mathfrak{B}} = (-F_{23}, -F_{31}, -F_{12})$, $\mathbf{X} = (X^1, X^2, X^3)$, $\mathbf{Y} = (Y^1, Y^2, Y^3)$, $\zeta c \rho_e = \zeta j_e^0 = j_e^0$, $\zeta \mathbf{j}_e = (j_e^1, j_e^2, j_e^3)$, $\zeta c \rho_m = \zeta j_m^0 = j_m^0$, $\zeta \mathbf{j}_m = (j_m^1, j_m^2, j_m^3)$. The coefficients $c = 1/\sqrt{\varepsilon_0 \mu_0}$ and $\zeta = \sqrt{\frac{\mu_0}{\varepsilon_0}}$ are introduced in the definitions of the three-dimensional variables so that in case the $\varkappa = 0$, $j_m^\mu = 0$, $Y^\mu = 0$, $\epsilon = 0$, Eqs. (15)-(18) coincide with Maxwell's equations, written down in SI unit system. In this case we postulate $\mathbf{\mathfrak{B}} = c\mathbf{B}$, $X^0 = \varphi$, $\mathbf{X} = c\mathbf{A}$ and use the constants c and ζ instead of the constants ε_0 and μ_0 . This form of Maxwell's equations allows us to use all the advantages of the Gaussian unit system, remaining at the same time in the SI unit system.

The following equalities

$$\frac{1}{c} \frac{\partial V^0}{\partial t} + \nabla \cdot \mathbf{V} + \varkappa \epsilon = 0, \quad (23)$$

$$\frac{1}{c} \frac{\partial \mathbf{V}}{\partial t} - \nabla \times \mathbf{U} + \nabla V^0 - \varkappa \mathbf{E} = 0, \quad (24)$$

$$\frac{1}{c} \frac{\partial \mathbf{U}}{\partial t} + \nabla \times \mathbf{V} + \nabla U^0 + \varkappa \mathbf{\mathfrak{B}} = 0, \quad (25)$$

$$\frac{1}{c} \frac{\partial U^0}{\partial t} + \nabla \cdot \mathbf{U} + \varkappa \beta = 0, \quad (26)$$

are satisfied due to the definitions (19)-(22). It may seem strange to introduce the fields V^μ and U^μ , which are

different from the potentials only by factor $\varkappa$. However, Eqs. (15)-(18) and (23)-(26) allow the introduction of the tensor, scalar and pseudoscalar potentials also. The fields V^μ and U^μ are connected with such potentials by differential relations like (19)-(20), and the fields ϵ , β , $\mathbf{E}$, $\mathbf{\mathfrak{B}}$ by the multiplier $\varkappa$. So, the fields V^μ , U^μ are connected with all potentials in the same way as the fields ϵ , β , $\mathbf{E}$, $\mathbf{\mathfrak{B}}$.

Substitution of the expressions (19)-(22) into Eqs. (15)-(18) yields equations (7) and (13) for the potentials.

The Eqs. (15)-(18) are the Euler equations for the Lagrangian

$$L = L_b + L_i, \quad (27)$$

$$L_b = \frac{1}{2\zeta} \left(-\frac{1}{2} F_{\alpha\beta} F^{\alpha\beta} - \epsilon^2 + \beta^2 + V_\alpha V^\alpha - U_\alpha U^\alpha \right) = \frac{1}{2\zeta} (E^2 - \mathfrak{B}^2 - \epsilon^2 + \beta^2 + V_0^2 - V^2 - U_0^2 + U^2), \quad (28)$$

$$L_i = -j_e^\alpha X_\alpha + j_m^\alpha Y_\alpha, \quad (29)$$

if we consider the potentials X^μ and Y^μ as independent variables. The interaction Lagrangian L_i describes the minimal interaction of the vector and pseudovector bosons X^μ , Y^μ with the currents j_e^α , j_m^α that produce them. Even if these currents are not conserved the propagators of bosons X^μ and Y^μ have the form (8).

The non-conserved currents are met in the study of the weak interaction. Let us use an example of the weak interaction of the charged currents in order to show the usefulness of the Eqs. (5), (11), (15)-(22) to describe the vector and pseudovector bosons.

In the Weinberg-Salam electroweak model the charged current interaction is given by the Lagrangian [1]:

$$L_i = -\frac{g}{2\sqrt{2}} \bar{e} \gamma^\mu (1 - \gamma^5) W_\mu^- \nu - \frac{g}{2\sqrt{2}} \bar{\nu} \gamma^\mu (1 - \gamma^5) W_\mu^+ e. \quad (30)$$

Here, $\gamma^5 = i\gamma^0\gamma^1\gamma^2\gamma^3$. The potentials W_μ^+ , W_μ^- describe the charged bosons. Let us show that the Lagrangian (30) coincides with (29), if we choose as the currents j_e^μ , j_m^μ the following combinations in Eq. (29):

$$j_e^\mu = \frac{g}{\sqrt{2}} (\bar{\nu} \gamma^\mu e + \bar{e} \gamma^\mu \nu), \quad (31)$$

$$j_m^\mu = i \frac{g}{\sqrt{2}} (\bar{\nu} \gamma^\mu \gamma^5 e - \bar{e} \gamma^\mu \gamma^5 \nu). \quad (32)$$

Really, the Lagrangian (29) for the currents (31)-(32) is the following:

$$L_i = -j_e^\mu X_\mu + j_m^\mu Y_\mu = -\frac{g}{\sqrt{2}} \left[(\bar{e} \gamma^\mu \nu + \bar{\nu} \gamma^\mu e) X_\mu + i (\bar{e} \gamma^\mu \gamma^5 \nu - \bar{\nu} \gamma^\mu \gamma^5 e) Y_\mu \right] =$$

$$\begin{aligned}
& -\frac{g}{\sqrt{2}} \left[\bar{e} \gamma^\mu (X_\mu + i\gamma^5 Y_\mu) \nu + \bar{\nu} \gamma^\mu (X_\mu - i\gamma^5 Y_\mu) e \right] = \\
& -\frac{g}{2\sqrt{2}} \bar{e} \gamma^\mu [(1 + \gamma^5) + (1 - \gamma^5)] (X_\mu + i\gamma^5 Y_\mu) \nu - \\
& -\frac{g}{2\sqrt{2}} \bar{\nu} \gamma^\mu [(1 + \gamma^5) + (1 - \gamma^5)] (X_\mu - i\gamma^5 Y_\mu) e = \\
& -\frac{g}{2\sqrt{2}} \bar{e} \gamma^\mu [(1 + \gamma^5)(X_\mu + iY_\mu) + (1 - \gamma^5)(X_\mu - iY_\mu)] \nu - \\
& -\frac{g}{2\sqrt{2}} \bar{\nu} \gamma^\mu [(1 + \gamma^5)(X_\mu - iY_\mu) + (1 - \gamma^5)(X_\mu + iY_\mu)] e. \quad (33)
\end{aligned}$$

Due to the fact that only the left neutrino exists, all terms with the factor $1 + \gamma^5$ are zeros, and Eq. (33) becomes:

$$L_i = -\frac{g}{2\sqrt{2}} \bar{e} \gamma^\mu (1 - \gamma^5) W_\mu^- \nu - \frac{g}{2\sqrt{2}} \bar{\nu} \gamma^\mu (1 - \gamma^5) W_\mu^+ e. \quad (34)$$

In this expression

$$W_\mu^- = X_\mu - iY_\mu, \quad W_\mu^+ = X_\mu + iY_\mu. \quad (35)$$

The Lagrangian (34) coincides with (30). The potentials W_μ^+ and W_μ^- are given by the combination of the Eqs. (7) and (13):

$$\begin{aligned}
\Box \frac{W^{+\mu}}{W^{-\mu}} + \kappa^2 \frac{W^{+\mu}}{W^{-\mu}} &= \frac{\zeta(j_e^\mu + ij_m^\mu)}{\zeta(j_e^\mu - ij_m^\mu)} = \frac{\zeta \frac{g}{\sqrt{2}} \bar{\nu} \gamma^\mu (1 - \gamma^5) e}{\zeta \frac{g}{\sqrt{2}} \bar{e} \gamma^\mu (1 - \gamma^5) \nu}. \quad (36)
\end{aligned}$$

We can introduce fields:

$$\mathbf{E}^\pm = -\frac{1}{c} \frac{\partial \mathbf{W}^\pm}{\partial t} - \nabla W_0^\pm \mp i \nabla \times \mathbf{W}^\pm, \quad (37)$$

$$\epsilon^\pm = -\frac{1}{c} \frac{\partial W_0^\pm}{\partial t} + \nabla \cdot \mathbf{W}^\pm, \quad V_\mu^\pm = -\kappa W_\mu^\pm. \quad (38)$$

These fields are determined from the equations

$$\frac{1}{c} \frac{\partial \epsilon^\pm}{\partial t} + \nabla \cdot \mathbf{E}^\pm - \kappa V_0^\pm = \zeta c \rho^\pm, \quad (39)$$

$$\frac{1}{c} \frac{\partial \mathbf{E}^\pm}{\partial t} \mp i \nabla \times \mathbf{E}^\pm + \nabla \epsilon^\pm + \kappa \mathbf{V}^\pm = -\zeta \mathbf{j}^\pm, \quad (40)$$

where $\rho^\pm = \rho_e \pm i\rho_m$, $\mathbf{j}^\pm = \mathbf{j}_e \pm i\mathbf{j}_m$. As can be seen the superpositions of the vector and pseudovector currents $j_e^\mu \pm ij_m^\mu$ create the potentials $W^{+\mu}$ and $W^{-\mu}$. Each superposition creates those potential, with which it interacts in Eq. (34). Though the currents (31) and (32) are not conserved, the propagators of the bosons $W^{+\mu}$ and $W^{-\mu}$ still have the same form (8).

It is also follows from Eq. (35) that the charged bosons can be considered as the superpositions of two states. These states are determined by the modified Maxwell's equations (15)-(18) with the currents (31) and (32). One of them is described by the vector potential X^μ , the other by the pseudovector potential Y^μ . These potentials interact minimally with the currents (31) and (32), respectively.

Thus, the bosons, the leptons and the weak interaction of their charged currents can be described by the Lagrangian

$$L = L_b + \hbar c L_l + L_i, \quad (41)$$

where

$$\begin{aligned}
L_l &= \frac{i}{2} (\bar{e} \gamma^\mu \frac{\partial e}{\partial x^\mu} - \frac{\partial \bar{e}}{\partial x^\mu} \gamma^\mu e) - \frac{m_e c}{\hbar} \bar{e} e + \\
&+ \frac{i}{2} (\bar{\nu} \gamma^\mu \frac{\partial \nu}{\partial x^\mu} - \frac{\partial \bar{\nu}}{\partial x^\mu} \gamma^\mu \nu). \quad (42)
\end{aligned}$$

It should be pointed out that the interaction Lagrangian in (41) can be used as (29), which is similar to the electrodynamics interaction Lagrangian. The boson propagator is different from the photon propagator by the mass term in the denominator only. That is why such interaction is renormalized. Because the Lagrangians (29) and (30) coincide, the results obtained with the Lagrangian (29) and obtained with the Weinberg-Salam model Lagrangian (30) coincide also.

Attention should be paid to the fact that the pseudovector current j_m^μ plays the role of the magnetic current in the modified Maxwell's equations (15)-(18). This leads our attention back to the Dirac hypothesis about the magnetic monopole [2]. Dirac introduced the magnetic current in analogy to the electric one — as a product of a magnetic charge and a velocity of a particle. Above, the magnetic current is introduced in a different way — as a product of the electric charge (the electric charge e is connected with the charge g , $g = e/\sin \theta_W$) and the pseudovector $i(\bar{\nu} \gamma^\mu \gamma^5 e - \bar{e} \gamma^\mu \gamma^5 \nu)$. In such a way, the magnetic monopole current is introduced without the magnetic monopole. The last definition does not require the introduction of magnetic monopole at all.

We do not touch on here other aspects of the weak interaction, as the aim of the article is to show the usefulness of use of the equations (5) and (11) instead of the Proca equation for the description of the vector and pseudovector bosons in the case of non-conserved current interactions.

Acknowledgments

The author would like to thank Prof. Lev B.I., Prof. Lukyanets S.P. and Prof. Zhmudskyy O.O. for stimulating discussions.

-
- [1] E. D. Commins and P. H. Bucksbaum, *Weak interactions of leptons and quarks* (Cambridge University Press, 1983). [2] P. A. . M. Dirac, Proc. Roy. Soc. London **A 133**, 60 (1931).